

MSW FMS908A



Self-powered IF Multiswitch. 8+1 inputs/ 8 outputs

Manufacturer: [Fagor](#)

Description

MODEL		FMS 908 A	FMS 912 A
Reference		86414	86420
Inputs		8 Sat. + 1 Terr	
Outputs		8	12
Frequency Range	Return Path Terr SAT	MHz 8 - 65 88 - 662 950 - 2150	
Gain	Return Path Terr Passive * Terr Active * SAT	-18 -20 3 ± 2,0 1 ± 2,0	-20 -22 3 ± 2,0 1 ± 2,0
Max. output level	Terr Active * SAT	DIN 45004B - 80 dB DIN 45004B - 35 dB	90 105
Rejection between	Terr to SAT SAT to Terr SAT - SAT	30 35 30	
Isolation between outputs		30	
Polarisation control		13/0dc / 19/0dc • 0 / 22 KHz	
Satellite control		Diasec2.0	
Max. LNBs current		mA 1000	
Input return losses		dB 10	
Output return losses		dB 10	
Connectors		F (f)	
Current consumption from receiver		mA - Max 70	
Supply voltage		Vdc 230 ± 15% / 50 Hz	
Power consumption	Terr Passive * without LNB Terr Active *	W 3,8 4,8	4,2 4,2
Operating temperature range		°C -10 à 55	
Packing dimensions		mm 337 x 131 x 63	458 x 131 x 63
Weight		Kg 1,42	1,42

* Terr Active or Passive selectable by switch.